

---

## Model No: CT-32E1

### Main Feature:

1. 24pcs  $\phi$  5 LED (IR distance 20 meters when IR on)
2. CDS Auto Control in Low Lux
3. Black plastic casing ,separated dual-glasses
4. ESD protection up to 5000-volt power supply
5. Voltage: DC-12V ,9 V to 15 V can be work normally
6. Day color , black and white at night
7. Strong Anti-noise function. Cable with copper jack
8. IR-CUT



### Specifications

Model No.	CT-32E1
CCD Sensor	1/3 CCD
CCTV SYSTEM	PAL
Number of pixels	PAL: 756(H) $\times$ 582(V)
Scanning System	PAL: 700 Lines, 50 Field/Sec
Sync System	Internal Synchronization
Horizontal Resolution	700TV Lines
Lens	3.6mm Lens
Usable illumination	0 LUX ( IR LED ON )
S/N Ratio	$\geq$ 55 dB
Gamma characteristic	0.45
Video output	1.0Vp-p, 75 ohm
Electronic Shutter time	Auto : 1/50~1/100,000Sec
Operation Temperature	-10 $\sim$ +50 RH95%Max
Storage Temperature	-20 $\sim$ +60 RH95%Max
Power supply	DC 12V $\pm$ 15%
Power Current	79mA IR LED off , 240mA IR LED On
Size	$\phi$ 86 x 90 ( H ) mm